

SCIENTIFIC REPORTS



OPEN

Magnetically tunable broadband transmission through a single small aperture

Received: 19 February 2015

Accepted: 01 July 2015

Published: 22 July 2015

Ke Bi¹, Wenjun Liu¹, Yunsheng Guo², Guoyan Dong³ & Ming Lei¹

Extraordinary transmission through a small aperture is of great interest. However, it faces a limitation that most of approaches can not realize the tunable transmission property, which is not benefit for the miniaturization of the microwave system. Here, we demonstrate a magnetically tunable broadband transmission through a small aperture. By placing two ferrite rods symmetrically on both sides of a single small aperture, the strongly localized electromagnetic fields are effectively coupled to the two ferrite rods. Both the simulated and experimental results indicate that such structure not only realizes a nearly total transmission through a small aperture, but also obtains a magnetically tunable property. This work offers new opportunities for the miniaturization of the microwave system.

Extraordinary transmission through a small aperture, drilled in an optically thick metal film, has stimulated tremendous interests due to its potential applications in the fields of flat optics, nanolithography, solar cells, fluorescence, chemical sensors, spectral filters, optical trapping, and second harmonic generation^{1–6}. Since Ebbesen *et al.*⁷ realized the extraordinary transmission from small aperture arrays that were milled in the thick metallic film, many configurations such as filling the hole with a material of high dielectric permittivity and placing artificially designed metamaterial covers in front of the aperture have been prepared to obtain efficient extraordinary transmission^{8–13}. Some published papers theoretically and experimentally explore the extraordinary transmission occurring through electrically small diaphragms placed inside hollow pipe waveguides^{14–19}. This work also considers this physical situation but adding ferrite elements to provide tunability. Aldin *et al.*²⁰ obtained 740-fold transmission enhancement by exciting the electric resonance of SRR. In previous studies, our group obtained 300-fold transmitted enhancement by using Mie-resonance coupling of two ceramic resonators²¹. Based on Bethe's theory²², light transmission through a single aperture of a radius $r \ll \lambda$ scales with $(r/\lambda)^4$. By using these configurations, the enhanced transmission which is more than that expected according to Bethe's theory can be obtained.

Recently, to realize the miniaturization of the microwave system, tunable devices have got a great deal of attention^{23,24}. Although many approaches on extraordinary transmission through a small aperture have been investigated, most of them can only realize the enhanced transmission at a certain frequency^{25–28}. When the structure is determined, the frequency of the enhanced transmission can not be changed, which is not benefit for the development of miniaturization technologies.

Here, we report a magnetically tunable enhanced transmission by using two ferrite rods placed symmetrically on both sides of a single small aperture. With a certain applied magnetic field, a broadband transmission is obtained at the resonance frequency because the coupling effect of the ferromagnetic resonances of the two ferrite rods. Moreover, the resonance frequency of the enhanced transmission can be tuned by the applied magnetic field, which is benefit for the miniaturization of the microwave devices.

¹State Key Laboratory of Information Photonics and Optical Communications & School of Science, Beijing University of Posts and Telecommunications, Beijing 100876, China. ²State Key Laboratory of New Ceramics and Fine Processing, School of Materials Science and Engineering, Tsinghua University, Beijing 100084, China. ³College of Materials Science and Opto-Electronic Technology, University of Chinese Academy of Sciences, Beijing 100049, China. Correspondence and requests for materials should be addressed to K.B. (email: bike@bupt.edu.cn), G.Y.D. (email: gydong@ucas.ac.cn) or M.L. (email: mlei@bupt.edu.cn)




Figure 1. Schematic diagrams of a small aperture in a metallic plate and ferrite rods. (a) Copper plate with small aperture. (b) Perspective view and (c) cross-section (yz -plane) of the two ferrite rods symmetrically placed on both sides of the aperture. The electromagnetic wave (8–12 GHz) propagates along y direction with an electric field polarized along the z direction. (d) Photograph of the fabricated ferrite rods.

Results

Design of the extraordinary transmission through a small aperture. Figure 1a shows the schematic diagram of a single small square aperture with a size of $3 \times 3 \times 1 \text{ mm}^3$ drilled at the center of a thin ($t = 1 \text{ mm}$) copper plate. To realize ferromagnetic resonance coupling, two ferrite rods are placed symmetrically on both sides of the aperture, which is shown in Fig. 1b,c. The distance between the two ferrite rods is 1 mm. The electromagnetic wave (8–12 GHz) propagates along y direction with an electric field polarized along the z direction. Obviously, the length of the side of the square aperture is much smaller than the wavelength. Figure 1d shows the photograph of the fabricated ferrite rods.

Ferromagnetic resonance can arise in ferrite when a bias magnetic field is applied. The resonance frequency can be expressed as follows²⁹:

$$\omega_r = \gamma \sqrt{[H + H_a + (N_x - N_z) 4\pi M_s][H + H_a + (N_y - N_z) 4\pi M_s]} \quad (1)$$

where γ is the gyromagnetic ratio, H is the applied magnetic field, H_a is the magnetocrystalline anisotropy field, M_s is the saturation magnetization caused by the applied magnetic field, N_x , N_y and N_z are the demagnetization factor for x , y and z directions, respectively. According to Eq. (1), the two ferrite rods have the same resonance frequency when their material parameters (H_a , N and M_s) and H are the same. Moreover, the resonance frequency can be tuned by the H , which means that we can control the ferromagnetic resonance by adjusting the applied magnetic field and further we can obtain the magnetically tunable ferromagnetic resonance.

Characterization of the proposed structure. In order to confirm the magnetically tunable behavior of ferromagnetic resonance, the transmission spectra for the ferrite rod was measured. Figure 2a shows the schematic experimental setup of a ferrite rod placed in the rectangular waveguide. The applied magnetic field H is along the z direction. The measured transmission spectra for the ferrite rod under a series of H are shown in Fig. 2b. When $H = 0$, there is no significant dip in transmission spectra, which indicates that no resonance takes place. When a magnetic field of $H = 3200 \text{ Oe}$ is applied, a prominent transmission dip appears at 10.1 GHz, which is induced by the negative permeability of the ferrite around the ferromagnetic resonance frequency³⁰. As H increases from 3200 Oe to 3600 Oe, the frequency of




Figure 2. Experiment demonstrating the magneto-tunable behavior of the ferrite rod. (a) Schematic experimental setup of a ferrite rod placed in the rectangular waveguide. The applied magnetic field is along the z direction. (b) Measured transmission spectra for the ferrite rod under a series of H .




Figure 3. Experiment demonstrating broadband transmission through a single small aperture. The black solid line represents the measured transmission spectrum for the metallic plate without ferrite rods. The navy short dashed line represents the transmission spectrum when two ferrite rods are placed in the rectangular waveguide. The red dashed line represents the transmission spectrum when only one ferrite rod is coupled with the metallic plate. The blue dotted line represents the transmission spectrum for the metallic plate with two ferrite rods. The bias magnetic field of 3400 Oe is applied. The inset shows the schematic experimental setup.

transmission dip increases, which exhibits a magnetically tunable behavior. In addition, a small transmission dip appears near the prominent dip, which can be attributed to the effect of the waveguide on ferrite rod.

Figure 3 shows the measured transmission spectra for a small aperture in a metallic plate with and without ferrite rods. The transmission spectrum for a small aperture in a metallic plate without ferrite rods is marked in black solid line. Because the length of the side of the square aperture is much smaller than the wavelength, the electromagnetic wave can not propagate through the metallic plate based on Bethe's theory. According to wireless energy transfer principle^{31,32}, two resonating objects with the same resonance frequency can exchange energy efficiently. Hence, by using the strong coupled ferromagnetic resonance, two ferrite rods with same material parameters were placed symmetrically on both sides of the aperture to realize the extraordinary transmission. The transmission spectrum for a small aperture in a metallic plate with ferrite rods is marked in blue dotted line. The inset shows the schematic experimental setup. The bias magnetic field of 3400 Oe is applied in the z direction. It can be seen that the transmission coefficients are above -2.5 dB over the frequency range from 9.25 to 9.6 GHz, indicating that a broadband transmission has been obtained. The maximum transmission coefficient is -0.98 dB at 9.32 GHz, which demonstrates that nearly all of the electromagnetic energy has transmitted through the




Figure 4. Experiment and simulation demonstrating magnetically tunable broadband transmission through a single small aperture. (a) Simulated transmission spectra for the small aperture with a series of side length a . (b) Measured transmission spectra for a small aperture in a metallic plate with ferrite rods under a series of H .

metallic plate. In addition, the transmission spectra when two ferrite rods are placed in the rectangular waveguide (marked in navy short dashed line) and when only one ferrite rod is coupled with the metallic plate (marked in red dashed line) are also shown in Fig. 3. Compared with the result shown in Fig. 2b, the ferromagnetic resonance when two ferrite rods are placed in the rectangular waveguide is stronger. It is obvious that the values of the spectrum for the metallic plate with two ferrite rods is much larger than that when only one ferrite rod is coupled with the metallic plate. Hence, the interaction between the two ferrite rods through the small aperture is much stronger than the other situations.

In order to understand the size effect of the aperture on the extraordinary transmission, the simulated transmission spectra for the small aperture with a series of side length a are shown in Fig. 4a. The bias magnetic field applied in the z direction is set at 3600 Oe. It can be seen that the frequency of transmission passband increases and the bandwidth becomes narrower as a decreases from 3 mm to 2.6 mm. To obtain the broadband property, the side length of 3 mm is chosen. Figure 4b shows the measured transmission spectra for a small aperture in a metallic plate with ferrite rods under a series of H . When $H = 0$, the values of the transmission coefficient are very low (about -33 db). Combined with the result shown in Fig. 2b, the reason is that there is no ferromagnetic resonance taking place. As H increases from 3200 Oe to 3600 Oe, the frequency of transmission passband increases, which indicates a magnetically tunable behavior. It can be seen that the tunable behavior observed here is in good agreement with that predicted in Eq. (1). The frequency of the transmission passband is inconsistent with that of ferromagnetic resonance shown in Fig. 2b, which is because the extraordinary transmission is induced by the interaction of ferrite rods and metallic plate perforated a small aperture. In addition, the maximum transmission coefficient increases from -0.98 db to -0.7 db, which demonstrates a nearly total transmission through a small aperture by ferromagnetic resonance coupling has been obtained. Note that this approach can not used in high frequency regions (THz, infrared or optical frequencies) due to the ferromagnetic resonance can not take place in these frequencies.

Electric energy density distributions. To corroborate the above measured and simulated results, we have simulated the electric energy density distributions of various structures. Figure 5a presents the electric energy density distribution in the xy -plane for a small aperture in a metallic plate without ferrite rods at 9.8 GHz. The incident wave is coming from the left, shooting normally onto the metallic plate. There is no wave appeared in the left area of the plate because the length of the side of the square aperture is much smaller than the wavelength. Figure 5b presents the electric energy density distribution in the xy -plane for a small aperture in a metallic plate with ferrite rods under applied magnetic field $H = 0$ Oe at 9.8 GHz. Since the ferromagnetic resonance can not take place in the ferrite rods, there is also no wave appeared in the left area of the plate. Figure 5c,d show the electric energy density distributions in the xy -plane for a small aperture in a metallic plate with ferrite rods under applied magnetic field $H = 3400$ Oe at 9.335 GHz and 9.8 GHz, respectively. From Fig. 5c, it can be seen that the electromagnetic wave propagates through the small aperture. The ferrite rod resonator acts as an antenna which can efficiently receive (or transmit) electromagnetic energy in (or into) the waveguide. When a bias magnetic field of 3400 Oe is applied, the electromagnetic fields are extremely localized at the two ferrite rods, and the strongly coupling effect of the ferromagnetic resonances between the rods produces a nearly total transmission through the small




Figure 5. Electric energy density distributions showing the transmission characteristic. (a) Simulated electric energy density distribution in the xy -plane for a small aperture in a metallic plate without ferrite rods at 9.8 GHz. Simulated electric energy density distributions in the xy -plane for a small aperture in a metallic plate with ferrite rods under applied magnetic field (b) $H = 0 \text{ Oe}$ at 9.8 GHz, (c) $H = 3400 \text{ Oe}$ at 9.335 GHz, (d) $H = 3400 \text{ Oe}$ at 9.8 GHz, (e) $H = 3600 \text{ Oe}$ at 9.335 GHz and (f) $H = 3600 \text{ Oe}$ at 9.8 GHz.

aperture. At 9.8 GHz, little electric energy density appears in the left area of the plate (shown in Fig. 5d), which is in good agreement with the transmission coefficient of -24.8 db shown in Fig. 4b. Figure 5e,f show the electric energy density distributions in the xy -plane for a small aperture in a metallic plate with ferrite rods under applied magnetic field $H = 3600 \text{ Oe}$ at 9.335 GHz and 9.8 GHz, respectively. In the left area of the plate, the intensities of the electric energy density at 9.335 GHz and 9.8 GHz are in good agreement with the transmission coefficients of -10 db and -1 db shown in Fig. 4b. One observes

that, as the H increases, the total transmission frequency increases. According to the above analysis, by using ferromagnetic resonance coupling between two ferrite rods, the magnetically tunable broadband transmission through a small aperture can be realized.

Discussion

We numerically and experimentally demonstrated a magnetically tunable broadband transmission through a small aperture by ferromagnetic resonance coupling. Due to the strongly localized electromagnetic fields of the two ferrite rods and the efficient coupling effect, the maximum transmission coefficient reaches -0.7 db, which demonstrates a nearly total transmission through a small aperture has been obtained. More importantly, the total transmission passband can be tuned by the magnetic field. This work provides a way to realize magnetically tunable broadband transmission through a small aperture, which has greater potential for the microwave devices.

Methods

Sample fabrication. The ferrite rods were synthesized by using yttrium iron garnet (YIG) ferrite with relative permittivity $\epsilon_r = 14.5$, saturation magnetization $4\pi M_s = 1950$ Oe and linewidth $\Delta H = 10$ Oe. The size of the YIG rods is $3 \times 3 \times 5$ mm³. The metallic plate was cut to dimension of $22.86 \times 10.16 \times 1$ mm³. The small square aperture with a size of $3 \times 3 \times 1$ mm³ was drilled at the center of the copper plate. The schematic diagrams of the proposed structure and the photograph of the ferrite rods are shown in Fig. 1.

Microwave measurements. The transmission spectra of the ferrite rod and the transmission through a small aperture with ferrite rods were measured by a microwave measurement system. The measurement system composed of a vector network analyzer (N5230C, Agilent Technologies, USA) and an electromagnet was shown in Ref. 33. The samples were placed in the X-band rectangular waveguides (22.86×10.16 mm²) and the waveguides were put in the middle of two magnets. By adjusted by input current, a bias magnetic field was generated around the samples along the z direction. The microwave propagated along y direction with the electric field along the z direction and the magnetic field along the x direction.

Simulations. The commercial time-domain package CST Microwave Studio TM was used to carried out the numerical predictions of the transmission spectra and electric energy density distributions. All the parameters of the ferrite rods and the metallic plate were the same as those in the experiments. The relative permittivity, saturation magnetization and linewidth of the ferrite rods are set as 14.5, 1950 Oe and 10 Oe, respectively. The models in the simulations were set up in accord with the actual measurement environment. The boundaries of the rectangular waveguide in the x and z directions are set as perfect electric.

References

- Dykhne, A., Sarychev, A. & Shalaev, V. Resonant transmittance through metal films with fabricated and light-induced modulation. *Phys. Rev. B* **67**, 195402 (2003).
- Shinada, S., Hashizume, J. & Koyama, F. Surface plasmon resonance on microaperture vertical-cavity surface-emitting laser with metal grating. *Appl. Phys. Lett.* **83**, 836–838 (2003).
- Ndao, A., Belkhir, A., Salut, R. & Baida, F. I. Slanted annular aperture arrays as enhanced-transmission metamaterials: Excitation of the plasmonic transverse electromagnetic guided mode. *Appl. Phys. Lett.* **103**, 211901 (2013).
- Guo, Y. & Zhou, J. Dual-band-enhanced Transmission through a Subwavelength Aperture by Coupled Metamaterial Resonators. *Sci. Rep.* **5**, 8144 (2015).
- Degiron, A., Lezec, H. J., Yamamoto, N. & Ebbesen, T. W. Optical transmission properties of a single subwavelength aperture in a real metal. *Opt. Commun.* **239**, 61–66 (2004).
- García-Vidal, F., Moreno, E., Porto, J. & Martín-Moreno, L. Transmission of Light through a Single Rectangular Hole. *Phys. Rev. Lett.* **95**, 103901 (2005).
- Ebbesen, T. W., Lezec, H. J., Ghaemi, H. F., Thio, T. & Wolff, P. A. Extraordinary optical transmission through sub-wavelength hole arrays. *Nature* **391**, 667–669 (1998).
- Webb, K. & Li, J. Analysis of transmission through small apertures in conducting films. *Phys. Rev. B* **73**, 033401 (2006).
- Lezec, H. J. *et al.* Beaming Light from a Subwavelength Aperture. *Science* **297**, 820–822 (2002).
- Akarca-Biyikli, S. S., Bulu, I. & Ozbay, E. Enhanced transmission of microwave radiation in one-dimensional metallic gratings with subwavelength aperture. *Appl. Phys. Lett.* **85**, 1098–1100 (2004).
- Martín-Moreno, L., García-Vidal, F., Lezec, H., Degiron, A. & Ebbesen, T. Theory of Highly Directional Emission from a Single Subwavelength Aperture Surrounded by Surface Corrugations. *Phys. Rev. Lett.* **90**, 167401 (2003).
- Hou, B., Wen, H., Leng, Y. & Wen, W. Electromagnetic wave transmission through subwavelength metallic meshes sandwiched between split rings. *Appl. Phys. Lett.* **87**, 201114 (2005).
- Fong, K.-Y. & Hui, P. M. Controlling enhanced transmission through metallic gratings with subwavelength slits by anisotropic waveguide resonance. *Appl. Phys. Lett.* **91**, 171101 (2007).
- Medina, F., Mesa, F. & Marqués, R. Extraordinary Transmission Through Arrays of Electrically Small Holes From a Circuit Theory Perspective. *IEEE Trans. Microw. Theory Tech.* **56** 108–3120 (2008).
- Gordon, R. Beth's aperture theory for arrays. *Phys. Rev. A* **76** 053806 (2007).
- Pang, Y., Hone, A. N., So, P. P. M. & Gordon, R. Total optical transmission through a small hole in a metal waveguide screen. *Opt. Express* **17** 4433–4441 (2009).
- Medina, F. *et al.* Experimental verification of extraordinary transmission without surface plasmons. *Appl. Phys. Lett.* **95** 071102 (2009).
- Kirilenko, A. A. & Perov, A. O. On the Common Nature of the Enhanced and Resonance Transmission Through the Periodical Set of Holes. *IEEE Trans. Antennas Propag.* **56** 3210–3216 (2008).

19. Medina, F., Mesa, F., Ruíz-Cruz, J. A., Rebollar, J. M. & Montejó-Garai, J. R. Study of Extraordinary Transmission in a Circular Waveguide System. *IEEE Trans. Microw. Theory Tech.* **58**, 1532–1542 (2010).
20. Aydin, K. *et al.* Split-Ring-Resonator-Coupled Enhanced Transmission through a Single Subwavelength Aperture. *Phys. Rev. Lett.* **102**, 013904 (2009).
21. Guo, Y., Zhou, J., Lan, C., Wu, H. & Bi, K. Mie-resonance-coupled total broadband transmission through a single subwavelength aperture. *Appl. Phys. Lett.* **104**, 204103 (2014).
22. Bethe, H. Theory of Diffraction by Small Holes. *Phys. Rev.* **66**, 163–182 (1944).
23. Kundu, A. *et al.* A tunable band-stop filter using a metamaterial structure and MEMS bridges on a silicon substrate. *J. Micromech. Microeng.* **22**, 045004 (2012).
24. Harward, I., Camley, R. E. & Celinski, Z. On-wafer magnetically tunable millimeter wave notch filter using M-phase Ba hexagonal ferrite/Pt thin films on Si. *Appl. Phys. Lett.* **105**, 173503 (2014).
25. Young, S. M., Pfeiffer, C. & Grbic, A. & Merlin, R. Enhanced resonant transmission of electromagnetic radiation through a pair of subwavelength slits. *Appl. Phys. Lett.* **103**, 041104 (2013).
26. García de Abajo, F. J. Light transmission through a single cylindrical hole in a metallic film. *Opt. Express* **10**, 1475–1484 (2002).
27. Hibbins, A. P., Sambles, J. R. & Lawrence, C. R. Gratingless enhanced microwave transmission through a subwavelength aperture in a thick metal plate. *Appl. Phys. Lett.* **81**, 4661–4663 (2002).
28. Lockyear, M. J., Hibbins, A. P. & Sambles, J. R. Transmission of microwaves through a stepped subwavelength slit. *Appl. Phys. Lett.* **91**, 251106 (2007).
29. Lax, B. & Button, K. J. *Microwave ferrites and ferrimagnetics* (McGraw-Hill, 1962).
30. Zhao, H., Zhou, J., Kang, L. & Zhao, Q. Tunable two-dimensional left-handed material consisting of ferrite rods and metallic wires. *Opt. Express* **17**, 13373–13380 (2009).
31. Kurs, A. *et al.* Wireless Power Transfer via Strongly Coupled Magnetic Resonances. *Science* **317**, 83–86 (2007).
32. Karalis, A., Joannopoulos, J. D. & Soljačić, M. Efficient wireless non-radiative mid-range energy transfer. *Ann. Phys.* **323**, 34–48 (2008).
33. Bi, K., Zhou, J., Liu, X., Lan, C. & Zhao, H. Multi-band negative refractive index in ferrite-based metamaterials. *Prog. Electromagn. Res.* **140**, 457–469 (2013).

Acknowledgements

This work was supported by the National Natural Science Foundation of China under Grant Nos 51402163, 61376018, 51032003, 11274198, 51102148 and 51221291; the China Postdoctoral Science Foundation under Grant Nos 2013M530042 and 2014T70075; and the Fundamental Research Funds for the Central Universities under Grant No. 2015RC18.

Author Contributions

K.B. conceived the idea and designed experiments. K.B., Y.S.G. and W.J.L. performed the experiments. K.B., G.Y.D. and S.G.H. developed the post-processing treatments of the experimental data. K.B. and M.L. carried out numerical calculations and figures. K.B. wrote the paper. All authors contributed to scientific discussion and critical revision of the article.

Additional Information

Competing financial interests: The authors declare no competing financial interests.

How to cite this article: Bi, K. *et al.* Magnetically tunable broadband transmission through a single small aperture. *Sci. Rep.* **5**, 12489; doi: 10.1038/srep12489 (2015).



This work is licensed under a Creative Commons Attribution 4.0 International License. The images or other third party material in this article are included in the article's Creative Commons license, unless indicated otherwise in the credit line; if the material is not included under the Creative Commons license, users will need to obtain permission from the license holder to reproduce the material. To view a copy of this license, visit <http://creativecommons.org/licenses/by/4.0/>